

Bendix King Scanning and Priority settings:

Toggles: Pulling the toggles toward you (toward the front of the radio) in most cases is turning the function "OFF". Pushing the toggles toward the radio is turning the function "ON".

Before selecting channels to be scanned and set as a priority, turn the PRI and SCAN toggle switches to the OFF position.

Select the channels to be scanned: You may wish to monitor several channels to listen for important information and updates. Turn the channel selector knob to the desired channel to scan and press the ENT key (SCN will appear in the LCD display). Repeat for each channel that you want to scan. You can scan as many channels as you wish, but only one channel can be set as a Priority. Push the SCAN toggle switch up to the on position to resume scanning. To remove a channel from the scan list, turn the SCAN and PRI toggle switches to the OFF position. Turn the channel selector knob to that channel and press the CLR key.

Priority scan enables the radio to scan and receive while monitoring for a message on the designated Priority Channel. You can only choose one channel to set for Priority. To select the Priority channel, turn the SCAN and PRI toggle switches to the OFF position. Turn the channel selector knob to the channel you choose for Priority and press the PRI key. Return the SCAN and PRI toggle switches to the ON position. Normally, channel 16 (NVADG) will be the designated Priority channel.

Changing Groups: Push the # key, then the number of the desired group, then press the ENT key. Example: #, 2, ENT. You're now in Group 2.